



46W 1050mA In-Door Settable Current LED Driver (compact type)

Product Offering



Order part number: SCA-AD-046W-1A05-A-PV-20-C

Product Description:

- Output current selectable by Dip-Switch with 8 levels selection and flickering Free
- Standby power ≤0.5W (1)
- AUX 12V output for drive other control module
- Dimming interface: 0-10V/1-10V; PWM (2)
- Nominal life 50,000hrs (at tc 65 °C with a failure rate <0.2% per 1,000hrs)

Feature:

- High efficiency with PF>0.95 and low THD <15% (typ.10%)
- Flickering free
- 0-10V/1-10V or PWM dimming interface (2)
- Fully protected: Short circuit, input voltage surge, overvoltage protection, over-temperature protection

Technical Data

Rated supply voltage, AC

AC Voltage range, AC

Survive input range (for 30mins)

DC Voltage Range, DC

Rated current @230Vac (with AUX)

Leakage current @240Vac

Max. input power (with AUX)

Typ. efficiency (at 230V 50Hz, full load)

Inrush current (at cold start, full load @230V)

Typ. λ (at 230 V 50Hz, Full load) Typ. λ (at 230 V 50Hz, Min. load)

Turn on time (at 230V 50Hz, full load)

Output rated power

Output current (selectable; ±5%)

Output Voltage (dc)

Output ripple current (100Hz)

DC AUX output

Dimming interface

Dimming level range

Surge Voltage

Ambient temperature ta Max. Casing temperature to

Size (mm) Weight

220-240 Vac, 50/60Hz

90-267 Vac, 50/60Hz

265-305 Vac, 50/60Hz

176-276V

<0.45A

<0.5mA@240Vac

55W

Typ. 89%

<20A (T-width <100µs)

>0.95

>0.7

< 0.5S (without dimming signal)

46.2W@1050mA, 44Vdc

700...1050mA (refer to current selection table)

20-44V

< 5% (typ.)

12V (1.5W max)

0-10V/1-10V; PWM (10V@100-3kHz)

0%, 10-100%

light industry level (surge 2KV)

-15 ... +50 °C

80 °C

175x49.5x31

270g

Output Current Selection Table

Output current selector



Current selection (8 levels)

Output current (± 5%)	Output Voltage range (Vdc)		Output Current Selector			
			1	2	3	4
1050mA	20	44	0	•	0	0
1000mA	20	44	0	•	0	•
950mA	20	44	0	•	•	0
900mA	20	44	0	•	•	•
850mA	20	44	•	0	0	0
800mA	20	44	•	0	0	•
750mA	20	44	•	0	•	0
700mA	20	44	•	0	•	•

Standard comply

EN55015; EN61000-3-2; EN61000-3-3; EN61547;


EN61347-1; EN61347-2-13; SELV






46W 1050mA In-Door Settable Current LED Driver (compact type)


Operation Output Diagram:






The above curve is for reference only and not represent the actual value

Dimming cable diagram:



0-10V/1-10V/PWM

Dimension and Product label:





- Remark:
 (1) Not included the AUX 12V output power.
 (2) Please ask sale department in detail if use PWM signal dimming.
 (3) The specification is subject to change witout notes.